

	Or Open	
C1B15:11	Sensor Supply Voltage B: Circuit Short To Ground	GO to Pinpoint Test C
C1B15:15	Sensor Supply Voltage B: Circuit Short To Battery or Open	GO to Pinpoint Test C
All other PDM Diagnostic Trouble Codes (DTCs)	-	REFER to: Locks, Latches and Entry Systems .

DIAGNOSIS AND TESTING > REAR VIEW MIRRORS > DTC CHART: IPMA

Diagnostics in this article assume a certain skill level and knowledge of Ford-specific diagnostic practices.
REFER to: Diagnostic Methods .

DTC	Description	Action
B1286:14	Interior Mirror: Circuit Short To Ground or Open	GO to Pinpoint Test G
All other IPMA Diagnostic Trouble Codes (DTCs)	-	REFER to: Lane Keeping System .

DIAGNOSIS AND TESTING > REAR VIEW MIRRORS > DTC CHART: FCIM

Diagnostics in this article assume a certain skill level and knowledge of Ford-specific diagnostic practices.
REFER to: Diagnostic Methods .

DTC	Description	Action
B1C83:12	Rear Defog Relay: Circuit Short to Battery	GO to Pinpoint Test D
B1C83:14	Rear Defog Relay: Circuit Short To Ground or Open	GO to Pinpoint Test D
All other FCIM Diagnostic Trouble Codes (DTCs)	-	Refer to the appropriate article for the procedure.

DIAGNOSIS AND TESTING > REAR VIEW MIRRORS > SYMPTOM CHART(S) > SYMPTOM CHART: REAR VIEW MIRRORS - EXTERIOR

Diagnostics in this article assume a certain skill level and knowledge of Ford-specific diagnostic practices.
REFER to: Diagnostic Methods .



NOTE: Clean the entire mirror assembly and glass to assist in verification of the customer concern and/or impact damage. Do not clean any mirror glass or housing with an ice scraper,